

# **NEW SIDEKICK PLUS® Testing G.fast**



# **NO MODULES NEEDED.**

Broadcom G.fast along with single and bonded ADSL/VDSL vectoring modem enables rapid installation without reboots.

# **NEW TECHNOLOGY**

# TIME-SAVINGS.

Easy to learn and use mode selection dial saves time and increases productivity on the job.


## FEATURE PACKED.

Robust copper test suite gualifies and troubleshoots xDSL up to 35MHz plus TDR/RFL.


# BONDED MODEM SIDEKICK PLUS TEST SET

### FOR PRODUCT VIDEOS, DEMONSTRATIONS AND MORE VISIT:

www.youtube.com/GreenleeDEMO



🕿 94% 🛛 🖸 G	.fast - S	howtime
Test	Up	Down
Link Rate	185832	767437
Max Rate	183293	767437
Capacity	100.0	100.0
SNR Margin	5.8	5.4
Power	4.0	4.0
Attenuation	0.0	0.0
INP	679.00	679.00
INT. Delay	0	0
Disconnect		▲Showtime




**BITS PER TONE** 

channel (frequency).

Shows the actual number

of bits on each pair that are

carried over each separate



#### HLOG DATA

Shows the attenuation per channel (frequency) between the DSLAM and the modems.

**SHOWTIME SYNC** While connecting to each pair, each bar will flash and turn solid upon sync. **SHOWTIME** Displays summary of vital xDSL information.

# **FEATURES**

#### G.FAST/SUPER-VECTORING/BONDED modem with xDSL:

- G.fast testing with full backwards compatibility on xDSL and Copper testing
- Two-pair bonding
- ADSL2+/VDSL2+
- Vectoring
- Broadcom 63138
- · Automated test scripts
- USB export/import of test results/profiles
- 35MHz Wideband Noise Spectrum Analysis
- 4.4MHz Loss Measurement Test
- 35MHz Impulse Noise Step TDR with Auto Bridge Tap Detection (Zero Dead Zone)

#### • ADSL/VDSL MODEM SYNC AND SERVICE TEST:

- > DSL Showtime
- > Upper Layer Testing (Ping, Trace-Route, HTTP)

> Quite Line Noise (QLN) Test

and FTP)

- > Bits per Tone> Signal-to-Noise Ratio
- > HLOG
- > Error Detect

### STANDARD:

- Advanced Dual Trace Pulse TDR (Zero Dead Zone)
- Resistive Fault Locator (Detects up to 20MΩ)
- 1GΩ Leakage Test (Insulation Resistance)
- Longitudinal Balance Test
- Ground Resistance Test
- Stress Test

- AC/DC Voltage
- Resistance
- Open Meter
- Loop Current
- Circuit Loss
- Tracing Tone Generator
- Reference Tone

### ORDERING INFORMATION

CAT NO.	DESCRIPTION
1155-5012	Sidekick® Plus with WIDEBAND & BONDED, LCC
1155-5013	Sidekick® Plus with WIDEBAND & BONDED, SCC
1155-5020	Sidekick® G.fast with WIDEBAND & BONDED

🔤 🖬 in У

#### WWW.GREENLEECOMMUNICATIONS.COM MA6656 03/17

1390 Aspen Way • Vista, CA 92081 • USA • 800.642.2155 ©2017 Greenlee Textron Inc. • An ISO 9001 Company • Printed in USA Greenlee Textron Inc. is a subsidiary of Textron Inc.